



## DESCRIPTION

**NT16BA09 HDbiT 1 TO 8 HDMI EXTENDER SPLITTER** This product combines the extender and splitter function to split 1 HDMI signal to 8 identical HDMI signals via network cable and it is used as a sender to work with 8 receivers to transmit these 8 HDMI signals up to 120meters. With the IR signal transmission to control the source device operation in long distance, it is widely applied in HD audio visual display room, HDTV, Set top box, DVD etc exhibition center and digital monitoring system.

# HDbiT 1 TO 8 HDMI EXTENDER SPLITTER

nT16BA09

## SPECIFICATION

IR signal	:	Support 20~60kHz IR device
input	:	1 x HDMI
output	:	8 x Rj45
connection indicator leds	:	8 x LED
power supply	:	DC12V/3A
power consumption	:	<24W
protection	:	Lightning protection Surge protection ESD protection
dimension	:	299(W) x 110.7(D) x 29.6(H)mm
weight	:	430g
color	:	Black



**INPUT 1xHDMI**  
**OUTPUT 8xRJ45**

**SUPPORT RESOLUTIONS**  
480I@60HZ, 480P@60HZ, 576I@50HZ, 576P@50HZ  
720P@50/60HZ, 1080I@50/60HZ, 1080P@50/60HZ



ADOPTING A NEW HIGH - DEFINITION DIGITAL TRANSMISSION TECHNOLOGY WITH LOWER DELAY AND MORE STABLE PERFORMANCE IT SPLITS ONE HDMI INPUT SIGNAL TO EIGHT HDMI OUTPUT SIGNALS IDENTICAL TO THE INPUT SIGNAL

Webpage



Youtube

